

Product Data Sheet

No. 87700 - 11/10

WIND 'N GO® EMERGENCY LIGHT & COMMUNICATION CENTER

PRODUCT NUMBER: 7700, 7701, 7702, 7703
7750, 7751, 7752, 7753



Patent Pending

I. GENERAL DESCRIPTION

Features: The Emergency Light & Communication Center are wall mounted charging stations that contain 2 or 3 self-powered Wind 'N Go Flashlights, BriteLights or 2-Way Radios (depending on model purchased). Power is continually supplied to the station by an AC power adapter to keep units charged. If the power goes out, they are ready to use for an extended period of time (see specifications on page 2). If the power is depleted, and the power has not been restored, it may be recharged by winding the handle for 1 minute to restore power in the rechargeable Lithium Ion battery. For complete information on the Wind 'N Go Flashlight, BriteLight, or 2-Way Radio/Flashlight please see their respective Product Data Sheets.

Other features include a power indicator light that illuminates when the power is on and blinks when the AC power goes out, charging indicator lights that turn green when the units are fully charged and turns red when the power is out or they are charging. Includes mounting instructions, mounting hardware, and a 120V AC/DC power adapter.

Benefits: When the power is out, light and communication is easily accessible and ready to use when stored in the Emergency Light & Communication Center. For extended periods of power disruption, back-up power is always available using the dynamo hand crank.

Uses: Dependable light and radio communication within easy reach. Ideal for power emergencies, building evacuations, poorly lit areas and home/office security.

Directions: Follow all instructions included with each specific Charging Center. Install within 3-4 feet from a 120V electrical outlet and in good sight. In a commercial setting, install the larger 3-Station Center anywhere where a lighted EXIT sign is required. Additional units are beneficial in the maintenance room, shop floor, and warehouse. The smaller 2-Station center is ideal for home or small business use. Install in the garage, laundry room, basement or store room.

Warnings: Read all instructions thoroughly prior to use. Avoid pointing the light at eyes. Remember to turn off when not in use and while charging. Units is water-resistant, but not waterproof. Do not submerge. Not intended for use in explosive atmospheres or locations.

Product Number Information:

P/N	Includes
7700	2 ea #7111 Flashlights
7701	1 ea #7111 Flashlight & 1 ea #7208 BriteLight
7702	2 ea #7208 BriteLights
7703	2 ea #7910 2-Way Radios
7750	3 ea #7111 Flashlights
7751	2 ea #7111 Flashlight & 1 ea #7208 BriteLight
7752	1 ea #7111 Flashlight & 2 ea #7208 BriteLight
7753	3 ea #7208 BriteLights

Accessories/Replacements:

#7111 Flashlight
#7208 BriteLight
#7910 2-Way Radio

Packaging:

2-Station Each box:	4 lbs. (1.8 kg)	0.28 CF (0.001 CM)	11.25" L x 3.375" W x 12.875" H
2-Station Case (2/case):	9 lbs. (4.1 kg)	0.67 CF (0.02 CM)	11.25" L x 8" W x 13" H
3-Station Each box:	5 lbs. (2.3 kg)	0.37 CF (0.01 CM)	14.25" L x 3.375" W x 13.5" H
3-Station Case (2/case):	11 lbs. (4.9 kg)	1.06 CF (0.03 CM)	15.0625" L x 8.25" W x 14.75" H



AerVOE Industries, Inc.
P.O. Box 485, Gardnerville, NV 89410



ZYNOLYTE



(775) 783-3100 Phone • (775) 782-5687 Fax • (800) 227-0196 Customer Service
www.aerVOE.com • www.athenabrands.com • www.zynolyte.com

II. DIAGRAM



Model #7703 shown

III. SPECIFICATIONS

Colors/Materials	Charging Center: Off white ABS plastic body & clear polycarbonate cover
.....	#7111 Flashlight: Yellow
.....	#7208 Britelight: Red
.....	#7910 2-Way Radio: Yellow
7111 & 7208 Flashlight Battery Information	Rechargeable Lithium Ion LIR14250/300 mAH 3.6V
7910 2-Way Radio Battery Information	Rechargeable Limit Ion LIR 123A/600 mAH 3.7V
Weight/Dimensions	2-Station: 1 lb. 14 oz. / 7.5" L x 3.25" W x 8.5" H
.....	3-Station: 2 lbs. 8 oz. / 10.625" L x 3.375" W x 9.25" H
AC/DC Charger	C-UL Approved Class 2 Transformer
.....	Input: 120V AC 60 Hz
.....	Output: 6V DC 300 mAH
.....	Replacement #7991 available.
DC Input	6V DC 300 mAH

POWER DURATION	FLASHLIGHT (#7111 only)	RADIO (#7208 only)	SIREN (#7208 only)	2-WAY RADIO (#7910 only)	
				2-WAY RADIO	FLASHLIGHT
Using the recharging center to fully charge: 1 unit = 6 hours 2-Station = 12 hours 3-Station = 18 hours	1 LED = 15 hrs 3 LED = 5 hrs	12 hrs	12 hrs	Stand-by time = 30-35 hrs	14 hrs
After winding for 1-3 minutes	1 LED = 60 min 3 LEDs = 30 min	25 min	30 min	PTT time = 1-2 hrs	30 min

IV. MISCELLANEOUS

Note: Batteries must be disposed of properly. Consult local disposal authority in your area for information.

V. WARRANTY

The statements made herein, on labels, product bulletins or by any of our employees or agents concerning this material are given for information only. Any liability whatsoever of Athena Brands to the user of the product, is limited to replacement of the product or purchase price refunded.